## **Technical Specification**

Trademark	Sharp	
Model ID	65BJ2K 65BJ3K 65BJ5K	
Energy efficiency class	A+	
Visible screen size (diagonal)	164 cm / 65 inches	
On-mode power consumption	118.0 W	
Annual energy consumption *1	172 kWh	
Standby power consumption *2	<0.50 W	
Off mode power consumption	n/a	
Screen resolution	3840 (H) x 2160 (V)	

1: Energy consumption XYZ kWh per year, based on the power consumption of the television operating 4 hours per day for 365 days. The actual energy consumption will depend on how the television is used. \*2: When the TV is turned off with the remote control/standby button and no function is active.

65BJ2K 65BJ3K 65BJ5K		
RF	75 ohm Antenna / Analog / DVB / Satellite	
Inputs	3 x HDMI, 3 x USB, 1 x SD card reader, 1 x RJ45 LAN/Ethernet, 1 x Mini -SCART, 1 x Mini Component/YPbPr, 1 x Mini AV IN - Composite Video/CVBS and L/R Audio shared for Composite Video and Component/YPbPr.	
Sound Outputs	1 x Digital Optical Audio output, 1 x 3.5mm Headphone	
Speaker*/ Amplifier Watts (RMS)	2 x 10 + 15W subwoofer	
Voltage and power consumption	AC 220V ~ 240V; 50Hz 118/155/180W (home mode/standard/max) (<0.5W in Standby)	
Dimensions including stand (mm)	1462W x 902H x 280D	
Net weight (Kgs)	21.0	
Wall Mounting	VESA 600 x 300 (mm)	

\*Built-in Harman Kardon speaker systems (Full-range speaker and tweeter).

#### harman/kardon

Harman Kardon is trademark of HARMAN International Industries, Incorporated, registered in the United States and/or other countries.

#### HDMI

The terms HDMI, HDMI High-Definition Multimedia Interface, and the HDMI Logo are trademarks or registered trademarks of HDMI Licensing Administrator, Inc.

item in the event of warranty/service repair is in it's original box/packaging. unable to carry out warranty/service if you are unable to package it correctly. The safest way to package your Please save your box/packaging as you will need this in the event of warranty/service repair or support. We are

be connected to the internet. Note that to use the full functionality of Freeview Play your set must

searching. of the major broadcasters and offers an alternative means of dramas and soaps, etc. Content is made up from recommendations Freeview Play Explore app features a carousel of genres to select from when searching for programmes, such as sport, comedy, Freeview Play brings together live TV viewing with "catch up" TV services such as BBC iPlayer, ITV player, More4 and Demand 5, The tuning will be placed in channel positions above 100. For example, 101 (BBC1 HD) 102 (BBC2 HD) etc. Please note that any Freeview HD channels found during

at www.freeview.co.uk. Freeview coverage area. You can check coverage for your postcode channels, you will need a Digital TV aerial and be in a good To receive Freeview channels, in particular Freeview HD

YDIGW-NO-STA

their content. If you decline an upgrade, you will not be able to access content that requires the upgrade. affect unprotected content or content protected by other content access technologies. Content owners may require you to upgrade PlayReady to access on content usage, content owners may require Microsoft to revoke the device's ability to consume PlayReady-protected content. Revocation should not uses PlayReady technology to access PlayReady-protected content and/or WMDRM-protected content. If the device fails to properly enforce restrictions Content owners use Microsoft Playkeady" content access technology to protect their intellectual property, including copyrighted content. This device

product is prohibited without the appropriate license(s) from Microsoft. This product contains technology subject to certain intellectual property rights of Microsoft. Use or distribution of this technology outside of this


Connecting Composite/AV - Mini Composite/AV Cable will be enough for both video and sound.

Yellow stays unconnected).

Connecting Component/YPbPr - you will need both the Mini YPbPr Cable and the Mini Composite/AV Cable



connect a device with SCART thurst of the TAACS iniM s'VT eth of Required if you wish to TAADS iniM





RF Cable



Judjuo 28V2\eiloompo2\VA connect a device with Aldis Composite/AV Cable

cables either from your retailer or at www.umc-uk.co.uk/cables Should you wish to connect older/analogue devices to your television, you can purchase the necessary

#### Additional Accessories

1 x Remote Control & 2 x AAA x S 1 x Stand installation pack 1 x Power Cable

1 x Safety Leaflet

1 x Quick Start Guide Included with this TV are the following accessories

Accessories

**L**PPIay

## what is included in the box

Settings > About 1 V > Help Intormation > View Unline Manual To launch the Online Manual, press the [MENU] button and then select:



# SHARP

## **Quick Start Set Up Guide**

For information on using the TV's features, please refer to the Operating Instructions.

**Model Numbers** 65BJ2K 65BJ3K 65BJ5K

Register your manufacturers guarantee

online within 14 days of purchase at

www.registertoday.co.uk/sharp

and enter into a prize draw to



#### Quick & easy guide for setting up your TV

What is included in the box Using the remote control Setting up the TV for the first time - including attaching the stand Connecting other devices to the Television

#### Need help setting up or using your TV?

Please contact the UK & ROI Helpline\* Telephone UK 0330 024 0803 or ROI 01443 3323 Online support at: www.umc-uk.co.uk Email support at: service@umc-uk.co.uk

\*Calls to 0330 numbers are charged at standard call rates and are included as part of any bundled minutes with your phone provider.

Calls to the ROI number are charged at the local call rate.

The telephone opening hours are Monday to Friday 8.30am to 6pm, Saturday 9am – 5pm.

Bank Holidays - 10am to 4pm


Closed Christmas and New Years day





to program it with the code 4170. your 5ky Q remote to operate the TV's basic functions, you will need you will need to program it with the code 2134. If you wish to use functions, you will need a 5ky remote control (Revision 9 or later) and If you wish to use your 5ky remote to operate the TV's basic

#### Sky Remote Code



FOR models with PVK Function. For models with integrated DVD players.

### 1 Fitting the stand

TV panel must be facing downwards.

For the stand installation, there is one type of screw provided as shown


To complete the stand installation you will require a cross head screw driver. Place the TV set on a flat and clean surface with the panel facing downwards to avoid damage.



Used for attaching the stand to the TV set (fig.2)



Place the TV set on a flat and clean surface with the panel facing downwards to avoid




When the stand feet are installed correctly the stand feet will be longest at the front of the TV and shortest at the back with the feet pointing away from each other.



When the stand/feet are in the correct position, secure the feet to the underside of the TV set using 4 screws provided.




### 2 Connecting your set



1) Connect the TV to your power socket.

2) If you wish to use the TV to receive Freeview/Saorview channels, connect the RF input from the TV to your outdoor Digital TV aerial. If you do not wish to receive Freeview/ Saorview, skip this step.

#### **3 Button Layout**



#### **4 Remote Control**

**Remote Control: Installing Batteries** 



Insert the batteries supplied into the remote control and press the standby button to power

## **Wall Mounting the TV**




Image for illustration only

- 1. Remove the four screws that are supplied in the wall mounting holes.
- 2. The wall mount can now be easily attached to the mounting holes on the rear of the TV.
- 3. Install the wall mounting bracket to the television as advised by the bracket manufacturer.

The picture shows the use of spacers, which are not applicable to all sets/installations.

## 5 First time installation Basic installation steps are shown below. These may vary slightly depending on model.



Introduction

When the set first turns on, it enters the First Time Installation mode. This can be restarted by restoring the set to default settings in the 'About TV' Menu

Note: In home mode the TV will switch off automatically after 4 hours in the event that no buttons are pressed on the TV or remote control. by pressing the [MENU] button and then selecting Settings>Time>Auto



**Environment of Use** 

Home Mode: For normal use, by default it is set to a power saving mode which reduces the energy used by up to 25% (by reducing the power to the LED/LCD panel). This can be changed in the picture mode settings.



**Default Source** 

Select the source which you use the most. If Digital TV (Freeview) is chosen, then at the next step, the set will tune in and default to Digital TV (Freeview). If one of the other sources is selected, then the set will not tune in at this stage and default to that input. If it is required to tune the set in later, press the [MENU] button and then select Settings>Channels



Select your preferred on-screen display language. This will change the language in which the menus and associated information is displayed in. When set up has been completed, to change this press the [MENU] button and then select Settings > System Menu > Language



You can connect the TV to your broadband router or wireless network in order to take advantage of the Smart functions. If you connect the TV to your router using an Ethernet cable (recommended) this step will be skipped.



Tune in Channels

Choose to install terrestrial channels now or later.



Select the correct flag for the country in which the set will be used in. This will enable the set to correctly install the functions applicable in the country of use.



Set Up Netflix

If you have a Netflix account, it can be set up on the television here. Once set up and validated, the First Time Installation returns to the next step.



#### **Support Advice**

Information regarding support is displayed for a little while. Tuning continues and a progress bar is shown with the number of channels found indicated below

If you are picking up signals from more than one transmitter, you will be requested to select your primary and secondary regions.

